LESCO DISTRIBUTING

ENERGIE

CAR AUDIO - CAR VIDEO - CAR SECURITY - CAR SAFETY - MARINE AUDIO - LED LIGHTING - CB RADIOS - AUTO ACCESSORIES - AND MUCH MORE.....

SPECIFICATIONS - PR SERIES

ENERGIE Model	Nominal Voltage	Amplifier Wattage	Weight lbs	Capacity Ah	Group Size	Positive Term	Optional Top Post
PR600	12	600	8	14	-	L	-
PR1000	12	1000	12	18	-	R	TPB6
PR1200	12	1200	12	18	-	R	TPB6
PR1600	12	1600	21	35	U-1	L	TPB6
PR1900	12	1900	18	28	-	R	TPB6
PR2400	12	2400	28	50	-	R	TPB6
PR2800	12	2800	34	55	22/51	L	TPB6
PR2800R	12	2800	34	55	22/51	**R**	TPB6
PR3600	12	3600	48	75	24	L	TPB6
PR3600R	12	3600	48	75	24	**R**	TPB6
PR4000	12	4000	59	90	27	L	TPB8
PR4800	12	4800	66	110	31	L	TPB8
PB34UH	12	NA	42	70	34	L	TPB6

	Power Cell Dimensions						
ENERGIE Model	Inches			Millimeters			Screw Dia.
	L	W	H	L	W	H	
PR600	5.94	3.86	3.82	151	98	97	5mm
PR1000	7.13	3.00	6.54	180	76	165	6mm
PR1200	7.13	3.03	6.57	181	77	166	6mm
PR1600	7.75	5.11	6.25	197	130	159	6mm
PR1900	6.54	6.89	4.92	166	175	125	6mm
PR2400	7.76	6.54	6.86	197	166	174	6mm
PR2800	9.02	5.43	8.27	229	138	210	6mm
PR2800R	9.02	5.43	8.27	229	138	210	6mm
PR3600	10.24	6.66	8.31	260	169	211	6mm
PR3600R	10.24	6.66	8.31	260	169	211	6mm
PR4000	12.10	6.66	8.31	307	169	211	8mm
PR4800	13.04	6.82	8.39	331	173	213	8mm
PB34UH	10.24	6.61	7.20	260	168	183	6mm

12 VOLT SMART DESULFATING CHARGER/MAINTAINER

RPS 5212

• Designed for any 12 volt lead acid battery from 28 AH up to 250 AH on SLI, SLA, VRLA, AGM, Gel, auto, marine, RV or powersport applications. • The charger is configured with polar mode to charge in extreme temperature conditions of 20° F or below, a recondition mode to desulfate low voltage batteries as well as a supply mode to power 12 volt devices with AC instead of batteries.• Users can enjoy peace of mind with the unit's polarity protection and batteries can be left connected to the charger to stay maintained. • 12V, 7.5AH, Cord Length: 6 Ft. AC power cord with a 14 ft. total reach from the AC outlet, Ring Terminals: 17 inch, Battery Clamps: 18 inch